

DGS-3120 SD Card Management Commands

Step1. Command “ss” could help us find relative commands.

```
DGS-3120-24TC Gigabit Ethernet Switch
Command Line Interface

Firmware: Build 1.01.B031
Copyright(C) 2010 D-Link Corporation. All rights reserved.
UserName:
Password:

DGS-3120-24TC:admin#ss
Available commands:
..                ?                cable_diag        cd
cfm               change          clear             config
copy             create          debug            del
delete           dir             disable           download
enable           erase           format           login
logout           md             move             no
ping             ping6          rd              reboot
reconfig         rename         reset            save
show            telnet        traceroute       traceroute6
upload

DGS-3120-24TC:admin#
```

Step2. Insert SD card, then you will find it shown as drive D.

```
DGS-3120-24TC:admin#dir c:
Command: dir c:

Directory of /c:

Idx Info      Attr Size      Update Time      Name
-----
 1 RUN        -rw- 5464952 2010/12/20 18:50:21 DGS3120_Run_1_01_B24.had
 2 RUN(b)     -rw- 5467716 2011/01/06 18:31:53 DGS3120_Run_1_01_027.had
 3 RUN        -rw- 5458840 2010/12/07 18:35:21 DGS3120_Run_1_00_026.had
 4 RUN(*)     -rw- 5469208 2011/02/21 10:49:50 DGS3120_Run_1_01_B031.had
 5 CFG(*)     -rw- 27145 2011/02/21 11:06:41 config.cfg
 6           d--- 0 2011/02/21 11:07:34 system

29618 KB total (8140 KB free)
(*) -with boot up info      (b) -with backup info

DGS-3120-24TC:admin#
DGS-3120-24TC:admin#dir d:
Command: dir d:

Directory of /d:

No file or directory under /d:

2027124 KB total (2027092 KB free)
(*) -with boot up info      (b) -with backup info

DGS-3120-24TC:admin#
```

Step3. Copy F/W_R1.01.27 from current drive C to SD card drive D.

```
DGS-3120-24TC:admin#dir c:
Command: dir c:

Directory of /c:

Idx Info      Attr Size      Update Time      Name
-----
 1 RUN        -rw- 5464952    2010/12/20 18:50:21 DGS3120_Run_1_01_B24.had
 2 RUN(b)    -rw- 5467716    2011/01/06 18:31:53 DGS3120_Run_1_01_027.had
 3 RUN        -rw- 5458840    2010/12/07 18:35:21 DGS3120_Run_1_00_026.had
 4 RUN(*)    -rw- 5469208    2011/02/21 10:49:50 DGS3120_Run_1_01_B031.had
 5 CFG(*)    -rw- 27145      2011/02/21 11:06:41 config.cfg
 6           d--- 0          2011/02/21 11:07:34 system

29618 KB total (8140 KB free)
(*) -with boot up info      (b) -with backup info

DGS-3120-24TC:admin#copy c: DGS3120_Run_1_01_027.had d: DGS3120_Run_1_01_027.had
Command: copy c: DGS3120_Run_1_01_027.had d: DGS3120_Run_1_01_027.had

Copying..... Done!

DGS-3120-24TC:admin#dir d:
Command: dir d:

Directory of /d:

Idx Info      Attr Size      Update Time      Name
-----
 1           -rw- 5467716    2011/02/21 11:27:12 DGS3120_Run_1_01_027.had

2027124 KB total (2021752 KB free)
(*) -with boot up info      (b) -with backup info

DGS-3120-24TC:admin#
```

Step4. Change boot_up F/W from current one stored in drive C to the one stored in drive D.

```
DGS-3120-24TC:admin#dir c:
Command: dir c:

Directory of /c:

Idx Info      Attr Size      Update Time      Name
-----
 1 RUN        -rw- 5464952    2010/12/20 18:50:21 DGS3120_Run_1_01_B24.had
 2 RUN(b)    -rw- 5467716    2011/01/06 18:31:53 DGS3120_Run_1_01_027.had
 3 RUN        -rw- 5458840    2010/12/07 18:35:21 DGS3120_Run_1_00_026.had
 4 RUN(*)    -rw- 5469208    2011/02/21 10:49:50 DGS3120_Run_1_01_B031.had
 5 CFG(*)    -rw- 27145      2011/02/21 11:06:41 config.cfg
 6           d--- 0          2011/02/21 11:07:34 system

29618 KB total (8140 KB free)
(*) -with boot up info      (b) -with backup info

DGS-3120-24TC:admin#config firmware image d:/DGS3120_Run_1_01_027.had boot_up
Command: config firmware image d:/DGS3120_Run_1_01_027.had boot_up

Success.
```

Step5. Confirm boot_up F/W was changed indeed.

```
DGS-3120-24TC:admin#dir d:
Command: dir d:

Directory of /d:

Idx Info   Attr Size   Update Time   Name
-----
1 RUN(*)   -rw- 5467716  2011/02/21 11:27:12 DGS3120_Run_1_01_027.had
2027124 KB total (2021752 KB free)
(*) -with boot up info      (b) -with backup info

DGS-3120-24TC:admin#dir c:
Command: dir c:

Directory of /c:

Idx Info   Attr Size   Update Time   Name
-----
1 RUN      -rw- 5464952  2010/12/20 18:50:21 DGS3120_Run_1_01_B24.had
2 RUN      -rw- 5467716  2011/01/06 18:31:53 DGS3120_Run_1_01_027.had
3 RUN      -rw- 5458840  2010/12/07 18:35:21 DGS3120_Run_1_00_026.had
4 RUN(b)   -rw- 5469208  2011/02/21 10:49:50 DGS3120_Run_1_01_B031.had
5 CFG(*)   -rw- 27145    2011/02/21 11:06:41 config.cfg
6          d--- 0         2011/02/21 11:07:34 system

29618 KB total (8139 KB free)
(*) -with boot up info      (b) -with backup info

DGS-3120-24TC:admin#
```

After reboot.

```
Boot Procedure                                     v1.00.009
-----
Power On Self Test ..... 100 %

MAC Address   : 1C-AF-F7-30-C9-E6
H/w version   : A1

Please wait, Loading v1.01.027 Runtime Image ..... 100 %
UART initL ..... 100 %
Starting runtime image
```

```
DGS-3120-24TC Gigabit Ethernet Switch
Command Line Interface

Firmware: Build 1.01.027
Copyright(C) 2010 D-Link Corporation. All rights reserved.
UserName:
Password:

DGS-3120-24TC:admin#dir d:
Command: dir d:

Directory of /d:

Idx Info   Attr Size   Update Time   Name
-----
1 RUN(*)   -rw- 5467716  2011/02/21 11:27:12 DGS3120_Run_1_01_027.had
2027124 KB total (2021752 KB free)
(*) -with boot up info      (b) -with backup info

DGS-3120-24TC:admin#dir c:
Command: dir c:

Directory of /c:

Idx Info   Attr Size   Update Time   Name
-----
1 RUN      -rw- 5464952  2010/12/20 18:50:21 DGS3120_Run_1_01_B24.had
2 RUN      -rw- 5467716  2011/01/06 18:31:53 DGS3120_Run_1_01_027.had
3 RUN      -rw- 5458840  2010/12/07 18:35:21 DGS3120_Run_1_00_026.had
4 RUN(b)   -rw- 5469208  2011/02/21 10:49:50 DGS3120_Run_1_01_B031.had
5 CFG(*)   -rw- 27145    2011/02/21 11:06:41 config.cfg
6          d--- 0         2011/02/21 11:41:59 system

29618 KB total (8139 KB free)
(*) -with boot up info      (b) -with backup info

DGS-3120-24TC:admin#
```


Step6. Copy configuration file “config.cfg” stored in drive C to drive D and named as “test.cfg”.

```
DGS-3120-24TC:admin#dir d:
Command: dir d:

Directory of /d:

Idx Info      Attr Size      Update Time      Name
-----
  1 RUN(*)  -rw- 5467716  2011/02/21 11:27:12 DGS3120_Run_1_01_027.had

2027124 KB total (2021752 KB free)
(*) -with boot up info      (b) -with backup info

DGS-3120-24TC:admin#
DGS-3120-24TC:admin#dir c:
Command: dir c:

Directory of /c:

Idx Info      Attr Size      Update Time      Name
-----
  1 CFG(*)  -rw- 27145   2011/02/21 11:45:51 config.cfg
  2 RUN     -rw- 5464952 2010/12/20 18:50:21 DGS3120_Run_1_01_B24.had
  3 RUN     -rw- 5467716 2011/01/06 18:31:53 DGS3120_Run_1_01_027.had
  4 RUN     -rw- 5458840 2010/12/07 18:35:21 DGS3120_Run_1_00_026.had
  5 RUN(b)  -rw- 5469208 2011/02/21 10:49:50 DGS3120_Run_1_01_B031.had
  6         d--- 0         2011/02/21 11:41:59 system

29618 KB total (8140 KB free)
(*) -with boot up info      (b) -with backup info

DGS-3120-24TC:admin#copy c: config.cfg d: test.cfg
Command: copy c: config.cfg d: test.cfg

Copying..... Done!

DGS-3120-24TC:admin#
DGS-3120-24TC:admin#dir d:
Command: dir d:

Directory of /d:

Idx Info      Attr Size      Update Time      Name
-----
  1 RUN(*)  -rw- 5467716  2011/02/21 11:27:12 DGS3120_Run_1_01_027.had
  2         -rw- 27145   2011/02/21 11:47:58 TEST.CFG

2027124 KB total (2021724 KB free)
(*) -with boot up info      (b) -with backup info
```

Step7. Change boot_up configuration from current one “config.cfg” stored in drive C to “test.cfg” stored in drive D.

```
DGS-3120-24TC:admin#dir c:
Command: dir c:

Directory of /c:

Idx Info      Attr Size      Update Time      Name
-----
1 CFG(*)      -rw- 27145      2011/02/21 11:45:51 config.cfg
2 RUN        -rw- 3464932    2010/12/20 18:30:21 DGS3120_Run_1_01_B24.had
3 RUN        -rw- 5467716    2011/01/06 18:31:53 DGS3120_Run_1_01_027.had
4 RUN        -rw- 5458840    2010/12/07 18:35:21 DGS3120_Run_1_00_026.had
5 RUN(b)     -rw- 5469208    2011/02/21 10:49:50 DGS3120_Run_1_01_B031.had
6           d--- 0          2011/02/21 11:41:59 system

29618 KB total (8140 KB free)
(*) -with boot up info      (b) -with backup info

DGS-3120-24TC:admin#dir d:
Command: dir d:

Directory of /d:

Idx Info      Attr Size      Update Time      Name
-----
1 RUN(*)      -rw- 5467716    2011/02/21 11:27:12 DGS3120_Run_1_01_027.had
2           -rw- 27145      2011/02/21 11:47:58 TEST.CFG

2027124 KB total (2021724 KB free)
(*) -with boot up info      (b) -with backup info

DGS-3120-24TC:admin#config configuration d:/TEST.CFG boot_up
Command: config configuration d:/TEST.CFG boot_up

Success.
```

```
DGS-3120-24TC:admin#dir d:
Command: dir d:

Directory of /d:

Idx Info      Attr Size      Update Time      Name
-----
1 RUN(*)      -rw- 5467716    2011/02/21 11:27:12 DGS3120_Run_1_01_027.had
2 CFG(*)      -rw- 27145      2011/02/21 11:47:58 TEST.CFG

2027124 KB total (2021724 KB free)
(*) -with boot up info      (b) -with backup info

DGS-3120-24TC:admin#dir c:
Command: dir c:

Directory of /c:

Idx Info      Attr Size      Update Time      Name
-----
1 CFG(b)      -rw- 27145      2011/02/21 11:45:51 config.cfg
2 RUN        -rw- 3464932    2010/12/20 18:30:21 DGS3120_Run_1_01_B24.had
3 RUN        -rw- 5467716    2011/01/06 18:31:53 DGS3120_Run_1_01_027.had
4 RUN        -rw- 5458840    2010/12/07 18:35:21 DGS3120_Run_1_00_026.had
5 RUN(b)     -rw- 5469208    2011/02/21 10:49:50 DGS3120_Run_1_01_B031.had
6           d--- 0          2011/02/21 11:41:59 system

29618 KB total (8139 KB free)
(*) -with boot up info      (b) -with backup info

DGS-3120-24TC:admin#
```

It will take effect after reboot.

Appendix.

#1. Delete designate file from designate drive.

```
DGS-3120-24TC:admin#dir c:
Command: dir c:

Directory of /c:

Idx Info      Attr Size      Update Time      Name
-----
 1 CFG(b)     -rw- 27145      2011/02/21 11:45:51 config.cfg
 2 RUN       -rw- 5464952    2010/12/20 18:50:21 DGS3120_Run_1_01_B24.had
 3 RUN       -rw- 5467716    2011/01/06 18:31:53 DGS3120_Run_1_01_027.had
 4 RUN       -rw- 5458840    2010/12/07 18:35:21 DGS3120_Run_1_00_026.had
 5 RUN(b)    -rw- 5469208    2011/02/21 10:49:50 DGS3120_Run_1_01_B031.had
 6           d--- 0           2011/02/21 11:41:59 system

29618 KB total (8139 KB free)
(*) -with boot up info      (b) -with backup info

DGS-3120-24TC:admin#
DGS-3120-24TC:admin#del c:/DGS3120_Run_1_00_026.had
Command: del c:/DGS3120_Run_1_00_026.had

Success.

DGS-3120-24TC:admin#
DGS-3120-24TC:admin#dir c:
Command: dir c:

Directory of /c:

Idx Info      Attr Size      Update Time      Name
-----
 1 CFG(b)     -rw- 27145      2011/02/21 11:45:51 config.cfg
 2 RUN       -rw- 5464952    2010/12/20 18:50:21 DGS3120_Run_1_01_B24.had
 3 RUN       -rw- 5467716    2011/01/06 18:31:53 DGS3120_Run_1_01_027.had
 4 RUN(b)    -rw- 5469208    2011/02/21 10:49:50 DGS3120_Run_1_01_B031.had
 5           d--- 0           2011/02/21 11:41:59 system

29618 KB total (13471 KB free)
(*) -with boot up info      (b) -with backup info

DGS-3120-24TC:admin#
```

Please notice that the command is **“del”**, not **“delete”**.

F/W R1.00.026 disappeared from drive C.

#2. Copy F/W R1.01.027 from SD card back to drive C and named as “abc.had”.

```
DGS-3120-24TC:admin#dir c:
Command: dir c:

Directory of /c:

Idx Info      Attr Size      Update Time      Name
-----
1 CFG(b)     -rw- 27145      2011/02/21 11:45:51 config.cfg
2 RUN        -rw- 5464952    2010/12/20 18:50:21 DGS3120_Run_1_01_B24.had
3 RUN        -rw- 5467716    2011/01/06 18:31:53 DGS3120_Run_1_01_027.had
4 RUN(b)     -rw- 5469208    2011/02/21 10:49:50 DGS3120_Run_1_01_B031.had
5           d--- 0          2011/02/21 11:41:59 system

29618 KB total (13471 KB free)
(*) -with boot up info      (b) -with backup info

DGS-3120-24TC:admin#
DGS-3120-24TC:admin#dir d:
Command: dir d:

Directory of /d:

Idx Info      Attr Size      Update Time      Name
-----
1 RUN(*)     -rw- 5467716    2011/02/21 11:27:12 DGS3120_Run_1_01_027.had
2 CFG(*)     -rw- 27145      2011/02/21 11:47:58 TEST.CFG

2027124 KB total (2021724 KB free)
(*) -with boot up info      (b) -with backup info

DGS-3120-24TC:admin#
DGS-3120-24TC:admin#copy d:/DGS3120_Run_1_01_027.had c:/abc.had
Command: copy d:/DGS3120_Run_1_01_027.had c:/abc.had

Copying..... Done!

DGS-3120-24TC:admin#dir c:
Command: dir c:

Directory of /c:

Idx Info      Attr Size      Update Time      Name
-----
1 RUN(b)     -rw- 5467716    2011/02/21 12:01:55 abc.had
2 CFG(b)     -rw- 27145      2011/02/21 11:45:51 config.cfg
3 RUN        -rw- 5464952    2010/12/20 18:50:21 DGS3120_Run_1_01_B24.had
4 RUN        -rw- 5467716    2011/01/06 18:31:53 DGS3120_Run_1_01_027.had
5 RUN        -rw- 5469208    2011/02/21 10:49:50 DGS3120_Run_1_01_B031.had
```

#3. Copy configuration file “test.cfg” from SD card back to drive C and named as “testtest.cfg”.

```
DGS-3120-24TC:admin#copy d:/test.cfg c:/testtest.cfg
Command: copy d:/test.cfg c:/testtest.cfg

Copying..... Done!

DGS-3120-24TC:admin#dir c:
Command: dir c:

Directory of /c:

Idx Info      Attr Size      Update Time      Name
-----
1 CFG(b)     -rw- 27145      2011/02/21 12:06:18 testtest.cfg
2 RUN(b)     -rw- 5467716    2011/02/21 12:01:55 abc.had
3 CFG        -rw- 27145      2011/02/21 11:45:51 config.cfg
4 RUN        -rw- 5464952    2010/12/20 18:50:21 DGS3120_Run_1_01_B24.had
5 RUN        -rw- 5467716    2011/01/06 18:31:53 DGS3120_Run_1_01_027.had
6 RUN        -rw- 5469208    2011/02/21 10:49:50 DGS3120_Run_1_01_B031.had
7           d--- 0          2011/02/21 11:41:59 system

29618 KB total (8102 KB free)
(*) -with boot up info      (b) -with backup info

DGS-3120-24TC:admin#
```