

Product Highlights

802.11N

High connection rate
(up to 300Mbps)
and superior wireless range

SECURITY

Multiple firewall functions, several
security standards for wireless
connection

IPV6 SUPPORT

All needed functions
for up-to-date networking

USB PORT

Support of USB modem for Internet
connection via 4G/3G/2G network,
USB storage, and printer



DIR-620S

Wireless N300 Router with 3G/LTE Support and USB Port

USB Port

The router is equipped with a USB port for connecting a USB modem, which can be used to establish connection to the Internet. In addition, to the USB port of the router you can connect a USB storage device, which will be used as a network drive, or a printer.

In order to use the multifunction USB port effectively, the router supports simultaneous operation of several USB devices. For example, you can access multimedia content of the connected HDD storage and at the same time share a USB printer.¹

LAN/WAN Conversion

You can use any Ethernet port of the router as LAN or WAN port. The new-generation firmware supports assigning several WAN ports, for example, in order to configure the primary and backup WAN connection of different ISPs. In addition, you can configure the WAN failover using a 3G/4G modem.

Wireless Interface

Using the DIR-620S device, you are able to quickly create a wireless network at home or in your office, which lets computers and mobile devices access the Internet virtually anywhere (within the operational range of your wireless network). The router can operate as a base station for connecting wireless devices of the standards 802.11b, 802.11g, and 802.11n (at the rate up to 300Mbps).

Secure Wireless Connection

The router supports multiple functions for the wireless interface: several security standards (WEP, WPA/WPA2), MAC address filtering, WPS, WMM.

In addition, the device is equipped with a button for switching the Wi-Fi network off/on. If needed, for example, when you leave home, you can easily switch the router's WLAN by pressing the button, and devices connected to the LAN ports of the router will stay online.

Advanced Capabilities of Wireless Network

Smart adjustment of Wi-Fi clients is useful for networks based on several D-Link access points or routers – when the smart adjustment function is configured on each of them, a client always connects to the access point (router) with the highest signal level.

Support of guest Wi-Fi network allows you to create a separate wireless network with individual security settings. Devices connected to the guest network will be able to access the Internet, but will be isolated from the devices and resources of the router's LAN.

¹ When using a USB hub with external power supply.

4-port Switch

The built-in 4-port switch enables you to connect Ethernet-enabled computers, game consoles, and other devices to your network.

Security

The wireless router DIR-620S includes a built-in firewall. The advanced security functions minimize threats of hacker attacks, prevent unwanted intrusions to your network, and block access to unwanted websites for users of your LAN.

Now the schedules are also implemented; they can be applied to the rules and settings of the firewall and used to reboot the router at the specified time or every specified time period and to enable/disable the wireless network and the Wi-Fi filter.

Easy configuration and update

You can configure the settings of the wireless router DIR-620S via the user-friendly web-based interface (the interface is available in several languages).

The configuration wizard allows you to quickly switch DIR-620S to one of the following modes: router (for connection to a wired or wireless ISP), access point, repeater, or client, and then configure all needed setting for operation in the selected mode in several simple steps.

Also DIR-620S supports configuration and management via mobile application for Android and iPhone smartphones.

You can simply update the firmware: the router itself finds approved firmware on D-Link update server and notifies when ready to install it.

| Hardware | |
|------------------------|---|
| Processor | <ul style="list-style-type: none"> · MT7628NN (580MHz) |
| RAM | <ul style="list-style-type: none"> · 64MB, DDR2 SDRAM |
| Flash | <ul style="list-style-type: none"> · 16MB, SPI |
| Interfaces | <ul style="list-style-type: none"> · 10/100BASE-TX WAN port · 4 10/100BASE-TX LAN ports · USB 2.0 port |
| LEDs | <ul style="list-style-type: none"> · Power · Internet · 1-4 LAN LEDs · WLAN · WPS · USB |
| Buttons | <ul style="list-style-type: none"> · POWER button to power on/power off · RESET button to restore factory default settings · WLAN/WPS button to set up wireless connection and enable/disable wireless network |
| Antenna | <ul style="list-style-type: none"> · Two external non-detachable antennas (5dBi gain) |
| MIMO | <ul style="list-style-type: none"> · 2 x 2 |
| Power connector | <ul style="list-style-type: none"> · Power input connector (DC) |

| Software | |
|-----------------------------|--|
| WAN connection types | <ul style="list-style-type: none"> · Mobile Internet (via supported USB modem) · PPPoE · IPv6 PPPoE · PPPoE Dual Stack · Static IPv4 / Dynamic IPv4 · Static IPv6 / Dynamic IPv6 · PPPoE + Static IP (PPPoE Dual Access) · PPPoE + Dynamic IP (PPPoE Dual Access) · PPTP/L2TP + Static IP · PPTP/L2TP + Dynamic IP |
| Network functions | <ul style="list-style-type: none"> · DHCP server/relay · Advanced configuration of built-in DHCP server · Stateful/Stateless mode for IPv6 address assignment, IPv6 prefix delegation · Automatic obtainment of LAN IP address (for access point/repeater/client modes) · DNS relay · Dynamic DNS · Static IPv4/IPv6 routing · IGMP Proxy · Support of UPnP IGD · Support of VLAN · WAN ping respond · Support of SIP ALG · Support of RTSP · LAN/WAN conversion · Multi-WAN support · WAN failover · Autonegotiation of speed, duplex mode, and flow control / Manual speed and duplex mode setup for each Ethernet port · Built-in UDPXY application · XUPNPD plug-in |
| Firewall functions | <ul style="list-style-type: none"> · Network Address Translation (NAT) · Stateful Packet Inspection (SPI) · IPv4/IPv6 filter · MAC filter · URL filter · DMZ · Virtual servers |

| Software | |
|----------------------------------|---|
| VPN | <ul style="list-style-type: none"> · IPsec/PPTP/L2TP/PPPoE pass-through |
| USB interface functions | <ul style="list-style-type: none"> · USB modem Auto connection to available type of supported network (4G/3G/2G) Auto configuration of connection upon plugging in USB modem Enabling/disabling PIN code check, changing PIN code² Sending/receiving/reading/removing SMS messages² Support of USSD requests² · USB storage File browser Print server Access to storage via accounts Built-in Samba/FTP/DLNA server Built-in Transmission torrent client; uploading/downloading files from/to USB storage |
| Management and monitoring | <ul style="list-style-type: none"> · Local and remote access to settings through TELNET/WEB (HTTP/HTTPS) · Multilingual web-based interface for configuration and management · Support of D-Link Assistant application for Android and iPhone smartphones · Notification on connection problems and auto redirect to settings · Firmware update via web-based interface · Automatic notification on new firmware version · Saving/restoring configuration to/from file · Support of logging to remote host/connected USB storage · Automatic synchronization of system time with NTP server and manual time/date setup · Ping utility · Traceroute utility · TR-069 client · SNMP agent · Schedules for rules and settings of firewall, automatic reboot, and enabling/disabling wireless network and Wi-Fi filter · Automatic upload of configuration file from ISP's server (Auto Provision) |

| Wireless Module Parameters | |
|---|--|
| Standards | <ul style="list-style-type: none"> · IEEE 802.11b/g/n |
| Frequency range <i>The frequency range depends upon the radio frequency regulations applied in your country</i> | <ul style="list-style-type: none"> · 2400 ~ 2483.5MHz |
| Wireless connection security | <ul style="list-style-type: none"> · WEP · WPA/WPA2 (Personal/Enterprise) · MAC filter · WPS (PBC/PIN) |
| Advanced functions | <ul style="list-style-type: none"> · Support of client mode · WMM (Wi-Fi QoS) · Information on connected Wi-Fi clients · Advanced settings · Smart adjustment of Wi-Fi clients · Guest Wi-Fi / support of MBSSID · Periodic scan of channels, automatic switch to least loaded channel · Autonegotiation of channel bandwidth in accordance with environment conditions (20/40 Coexistence) · Support of STBC |
| Wireless connection rate | <ul style="list-style-type: none"> · IEEE 802.11b: 1, 2, 5.5, and 11Mbps · IEEE 802.11g: 6, 9, 12, 18, 24, 36, 48, and 54Mbps · IEEE 802.11n: from 6.5 to 300Mbps (from MCS0 to MCS15) |

² For some models of USB modems.

| Wireless Module Parameters | |
|---|--|
| <p>Transmitter output power</p> <p><i>The maximum value of the transmitter output power depends upon the radio frequency regulations applied in your country</i></p> | <ul style="list-style-type: none"> · 802.11b (typical at room temperature 25 °C) 15dBm (+/-2dB) at 1, 2, 5.5, 11Mbps · 802.11g (typical at room temperature 25 °C) 15dBm (+/-2dB) at 6~12, 18~24, 36, 48, 54Mbps · 802.11n (typical at room temperature 25 °C) HT20/HT40 15dBm (+/-2dB) at MCS0~7 |
| <p>Receiver sensitivity</p> | <ul style="list-style-type: none"> · 802.11b (typical at PER = 8% at room temperature 25 °C) -80dBm at 1Mbps -80dBm at 2Mbps -76dBm at 5.5Mbps -76dBm at 11Mbps · 802.11g (typical at PER = 10% at room temperature 25 °C) -82dBm at 6Mbps -81dBm at 9Mbps -79dBm at 12Mbps -77dBm at 18Mbps -74dBm at 24Mbps -70dBm at 36Mbps -66dBm at 48Mbps -65dBm at 54Mbps · 802.11n (typical at PER = 10% at room temperature 25 °C) HT20 -82dBm at MCS0 -79dBm at MCS1 -77dBm at MCS2 -74dBm at MCS3 -70dBm at MCS4 -66dBm at MCS5 -65dBm at MCS6 -64dBm at MCS7 HT40 -79dBm at MCS0 -76dBm at MCS1 -74dBm at MCS2 -71dBm at MCS3 -67dBm at MCS4 -63dBm at MCS5 -62dBm at MCS6 -61dBm at MCS7 |
| <p>Modulation schemes</p> | <ul style="list-style-type: none"> · 802.11b: DQPSK, DBPSK, DSSS, and CCK · 802.11g: BPSK, QPSK, 16QAM, 64QAM with OFDM · 802.11n: BPSK, QPSK, 16QAM, 64QAM with OFDM |

| Physical Parameters | |
|------------------------|--|
| Dimensions (L x W x H) | · 141 x 100 x 32 mm (5.5 x 3.9 x 1.2 in) |

| Operating Environment | |
|-----------------------|---|
| Power | · Output: 12V DC, 1A |
| Temperature | · Operating: from 0 to 40 °C · Storage: from -20 to 65 °C |
| Humidity | · Operating: from 10% to 90% (non-condensing) · Storage: from 5% to 95% (non-condensing) |

| Delivery Package | |
|---|--|
| <ul style="list-style-type: none"> · Router DIR-620S · Power adapter DC 12V/1A · Ethernet cable · "Quick Installation Guide" (brochure) | |

| Supported USB modems ³ | |
|-----------------------------------|---|
| GSM | <ul style="list-style-type: none"> · Alcatel X500 · D-Link DWM-152C1 · D-Link DWM-156A6 · D-Link DWM-156A7 · D-Link DWM 156A8 · D-Link DWM-156C1 · D-Link DWM-157B1 · D-Link DWM-157B1 (Velcom) · D-Link DWM-158D1 · D-Link DWR-710 · Huawei E150 · Huawei E1550 · Huawei E156G · Huawei E160G · Huawei E169G · Huawei E171 · Huawei E173 (Megafon) · Huawei E220 · Huawei E3131 (MTS 420S) · Huawei E352 (Megafon) · Huawei E3531 · Prolink PHS600 · Prolink PHS901 · ZTE MF112 · ZTE MF192 · ZTE MF626 · ZTE MF627 · ZTE MF652 · ZTE MF667 · ZTE MF668 · ZTE MF752 |

³ The manufacturer does not guarantee proper operation of the router with every modification of the firmware of USB modems.

Supported USB modems

| | |
|--|---|
| LTE | <ul style="list-style-type: none">· Alcatel IK40V· D-Link DWM-222· Huawei E3131· Huawei E3272· Huawei E3351· Huawei E3372s· Huawei E3372h-153· Huawei E367· Huawei E392· Megafon M100-1· Megafon M100-2· Megafon M100-3· Megafon M100-4· Megafon M150-1· Megafon M150-2· Quanta 1K6E (Beeline 1K6E)· MTS 824F· MTS 827F· Yota LU-150· Yota WLTUBA-107· ZTE MF823· ZTE MF823D· ZTE MF827· ZTE MF833T· ZTE MF833V |
| Smartphones in USB tethering mode | <ul style="list-style-type: none">· Some models of Android smartphones |