

Product Highlights

HIGH POWER AND SPEED

New dual core (880MHz),
Gigabit Ethernet ports,
total wireless connection rate up to
2100Mbps¹

EXTREME WI-FI PERFORMANCE

MU-MIMO for best rates, 4 data
streams for increased throughput

IPV6 SUPPORT

All needed functions
for up-to-date networking

TWO USB PORTS (2.0/3.0)

Support of USB modem for Internet
connection via 4G/3G/2G network,
USB storage, and printer



DIR-2150

AC2100 MU-MIMO Wi-Fi Gigabit Router with 3G/LTE Support and 2 USB Ports

USB Ports

The router is equipped with two USB ports for connecting a USB modem, a USB storage device or a printer. You are able to quickly connect to the Internet via a USB modem and use a USB storage device as a network drive.

In order to use multifunction USB ports effectively, the router supports simultaneous operation of several USB devices. For example, you can access multimedia content of the connected HDD storage and at the same time share a USB printer.

LAN/WAN Conversion, WAN Failover

You can use any Ethernet port of the router as LAN or WAN port. The new-generation firmware supports assigning several WAN ports, for example, in order to configure the primary and backup WAN connection of different ISPs. In addition, you can configure the WAN failover using a 3G/4G modem.

Wireless Interface

Using the DIR-2150 device, you are able to quickly create a high-speed wireless network at home or in your office, which lets computers and mobile devices access the Internet virtually anywhere (within the operational range of your wireless network). Simultaneous activity of 2.4GHz band and 5GHz band allows performing a wide range of tasks. The router can operate as a base station for connecting wireless devices of the standards 802.11a, 802.11b, 802.11g, 802.11n, and 802.11ac (at the wireless connection rate up to 2100Mbps¹).

Secure Wireless Connection

The router supports multiple functions for the wireless interface: several security standards (WEP, WPA/WPA2/WPA3), MAC address filtering, WPS, WMM.

In addition, the device is equipped with a button for switching the Wi-Fi network off/on. If needed, for example, when you leave home, you can easily switch the router's WLAN by pressing the button, and devices connected to the LAN ports of the router will stay online.

¹ Up to 300Mbps for 2.4GHz and up to 1733Mbps for 5GHz.

Advanced Capabilities of Wireless Network

Multi-user MIMO technology allows to distribute the router's resources to let multiple wireless clients use the Wi-Fi network efficiently, keeping high rates for HD media streaming, lag-free gaming, and fast transfer of large files.

Transmit Beamforming technology allows to flexibly change the antennas' radiation pattern and to redistribute the signal directly to wireless devices connected to the router.

Smart adjustment of Wi-Fi clients is useful for networks based on several D-Link access points or routers – when the smart adjustment function is configured on each of them, a client always connects to the access point (router) with the highest signal level.

Support of guest Wi-Fi network allows you to create a separate wireless network with individual security settings. Devices connected to the guest network will be able to access the Internet, but will be isolated from the devices and resources of the router's LAN.

Security

The wireless router DIR-2150 includes a built-in firewall. The advanced security functions minimize threats of hacker attacks, prevent unwanted intrusions to your network, and block access to unwanted websites for users of your LAN.

The SSH protocol support provides more secure remote configuration and management of the router due to encryption of all transmitted traffic, including passwords.

In addition, the router supports IPsec and allows to create secure VPN tunnels. Support of the IKEv2 protocol allows to provide simplified message exchange and use asymmetric authentication engine upon configuration of an IPsec tunnel.

Built-in Yandex.DNS service protects against malicious and fraudulent web sites and helps to block access to adult content on children's devices.

The router also supports the SkyDNS web content filtering service, which provides more settings and opportunities for safer Internet experience for home users of all ages and for professional activities of corporate users.

Now the schedules are also implemented; they can be applied to the rules of various filters and used to reboot the router at the specified time or every specified time period and to enable/disable the wireless network.

Easy configuration and update

You can configure the settings of the wireless router DIR-2150 via the user-friendly web-based interface (the interface is available in several languages).

The configuration wizard allows you to quickly switch DIR-2150 to one of the following modes: router (for connection to a wired or wireless ISP), access point, repeater, or client, and then configure all needed setting for operation in the selected mode in several simple steps.

Also DIR-2150 supports configuration and management via mobile application for Android and iPhone smartphones.

You can simply update the firmware: the router itself finds approved firmware on D-Link update server and notifies when ready to install it.

Hardware	
Processor	<ul style="list-style-type: none"> MT7621DAT (880MHz, dual core)
RAM	<ul style="list-style-type: none"> 128MB, DDR3
Flash	<ul style="list-style-type: none"> 128MB, NAND
Interfaces	<ul style="list-style-type: none"> 10/100/1000BASE-T WAN port 4 10/100/1000BASE-T LAN ports USB 2.0 port USB 3.0 port
LEDs	<ul style="list-style-type: none"> Power Internet WLAN 2.4G WLAN 5G
Buttons	<ul style="list-style-type: none"> POWER button to power on/power off RESET button to restore factory default settings WPS button to set up wireless connection and enable/disable wireless network
Antenna	<ul style="list-style-type: none"> Four external non-detachable antennas (5dBi gain)
MIMO	<ul style="list-style-type: none"> 4 x 4, MU-MIMO
Power connector	<ul style="list-style-type: none"> Power input connector (DC)

Software	
WAN connection types	<ul style="list-style-type: none"> Mobile Internet PPPoE IPv6 PPPoE PPPoE Dual Stack Static IPv4 / Dynamic IPv4 Static IPv6 / Dynamic IPv6 PPPoE + Static IP (PPPoE Dual Access) PPPoE + Dynamic IP (PPPoE Dual Access) PPTP/L2TP + Static IP PPTP/L2TP + Dynamic IP
Network functions	<ul style="list-style-type: none"> DHCP server/relay Advanced configuration of built-in DHCP server Stateful/Stateless mode for IPv6 address assignment, IPv6 prefix delegation Automatic obtainment of LAN IP address (for access point/repeater/client modes) DNS relay Dynamic DNS Static IP routing Static IPv6 routing IGMP/MLD Proxy RIP Support of UPnP IGD Support of VLAN WAN ping respond Support of SIP ALG Support of RTSP WAN failover LAN/WAN conversion Multi-WAN support Autonegotiation of speed, duplex mode, and flow control / Manual speed and duplex mode setup for each Ethernet port Built-in UDPXY application XUPNPD plug-in Equal load distribution while using several WAN connections (traffic balancing) Support of VRRP
Firewall functions	<ul style="list-style-type: none"> Network Address Translation (NAT) Stateful Packet Inspection (SPI) IP filter IPv6 filter MAC filter URL filter Ad blocking function DMZ Virtual servers Built-in Yandex.DNS web content filtering service Built-in SkyDNS web content filtering service

Software	
VPN	<ul style="list-style-type: none"> · IPsec/PPTP/L2TP/PPPoE pass-through · PPTP/L2TP servers · PPTP/L2TP tunnels · L2TP over IPsec · GRE tunnels, EoGRE tunnels · IPsec tunnels · Transport/Tunnel mode · IKEv1/IKEv2 support · DES encryption · NAT Traversal · Support of DPD (Keep-alive for VPN tunnels)
USB interface functions	<ul style="list-style-type: none"> · USB modem · Auto connection to available type of supported network (4G/3G/2G) · Auto configuration of connection upon plugging in USB modem · Enabling/disabling PIN code check, changing PIN code² · Sending/receiving/reading/removing SMS messages² · Support of USSD requests² · USB storage · File browser · Print server · Access to storage via accounts · Built-in Samba/FTP/DLNA server · Built-in Transmission torrent client; uploading/downloading files from/to USB storage
Management and monitoring	<ul style="list-style-type: none"> · Local and remote access to settings through SSH/TELNET/WEB (HTTP/HTTPS) · Multilingual web-based interface for configuration and management · Support of D-Link Assistant application for Android and iPhone smartphones · Notification on connection problems and auto redirect to settings · Firmware update via web-based interface · Automatic notification on new firmware version · Saving/restoring configuration to/from file · Support of logging to remote host/connected USB storage · Automatic synchronization of system time with NTP server and manual time/date setup · Ping utility · Traceroute utility · TR-069 client · SNMP agent · Schedules for filters rules, automatic reboot, and enabling/disabling wireless network · Automatic upload of configuration file from ISP's server (Auto Provision)

Wireless Module Parameters	
Standards	<ul style="list-style-type: none"> · IEEE 802.11a/n/ac · IEEE 802.11b/g/n · IEEE 802.11k/v
Frequency range <i>The frequency range depends upon the radio frequency regulations applied in your country</i>	<ul style="list-style-type: none"> · 2400 ~ 2483.5MHz · 5150 ~ 5350MHz · 5650 ~ 5850MHz
Wireless connection security	<ul style="list-style-type: none"> · WEP · WPA/WPA2 (Personal/Enterprise) · WPA3 (Personal) · MAC filter · WPS (PBC/PIN)
Advanced functions	<ul style="list-style-type: none"> · Support of client mode · WMM (Wi-Fi QoS) · Information on connected Wi-Fi clients · Advanced settings · Smart adjustment of Wi-Fi clients · Guest Wi-Fi / support of MBSSID · Periodic scan of channels, automatic switch to least loaded channel · Support of 802.11ac (5GHz) TX Beamforming · Wider bandwidth (up to 160MHz) · Autonegotiation of channel bandwidth in accordance with environment conditions (20/40 Coexistence) · Support of STBC

² For some models of USB modems.

Wireless Module Parameters	
Wireless connection rate	<ul style="list-style-type: none"> IEEE 802.11a: 6, 9, 12, 18, 24, 36, 48, and 54Mbps IEEE 802.11b: 1, 2, 5.5, and 11Mbps IEEE 802.11g: 6, 9, 12, 18, 24, 36, 48, and 54Mbps IEEE 802.11n (2.4GHz): from 6.5 to 300Mbps (from MCS0 to MCS15) IEEE 802.11n (5GHz): from 6.5 to 600Mbps (from MCS0 to MCS30) IEEE 802.11ac (5GHz): from 6.5 to 1733Mbps (from MCS0 to MCS9)
Transmitter output power <i>The maximum value of the transmitter output power depends upon the radio frequency regulations applied in your country</i>	<ul style="list-style-type: none"> 802.11a (typical at room temperature 25 °C) 15dBm 802.11b (typical at room temperature 25 °C) 15dBm 802.11g (typical at room temperature 25 °C) 15dBm 802.11n (typical at room temperature 25 °C) 2.4/5GHz 15dBm 802.11ac (typical at room temperature 25 °C) 15dBm
Receiver sensitivity	<ul style="list-style-type: none"> 802.11a (typical at PER < 10% (1000-byte PDUs) at room temperature 25 °C) -93.5dBm 802.11b (typical at PER = 8% (1000-byte PDUs) at room temperature 25 °C) -97dBm 802.11g (typical at PER < 10% (1000-byte PDUs) at room temperature 25 °C) -77dBm 802.11n (typical at PER = 10% (1000-byte PDUs) at room temperature 25 °C) 2.4GHz -72dBm 5GHz -70.5dBm 802.11ac (typical at PER = 10% (1000-byte PDUs) at room temperature 25 °C) -60.5dBm
Modulation schemes	<ul style="list-style-type: none"> 802.11a: BPSK, QPSK, 16QAM, 64QAM with OFDM 802.11b: DQPSK, DBPSK, DSSS, CCK 802.11g: BPSK, QPSK, 16QAM, 64QAM with OFDM 802.11n: BPSK, QPSK, 16QAM, 64QAM, 256QAM with OFDM 802.11ac: BPSK, QPSK, 16QAM, 64QAM, up to 256QAM with OFDM

Physical Parameters	
Dimensions (L x W x H)	<ul style="list-style-type: none"> 132 x 205 x 36 mm (5.19 x 8.07 x 1.4 in)
Weight	<ul style="list-style-type: none"> 340 g (0.75 lb)

Operating Environment	
Power	<ul style="list-style-type: none"> Output: 12V DC, 2A
Temperature	<ul style="list-style-type: none"> Operating: from 0 to 40 °C Storage: from -20 to 65 °C
Humidity	<ul style="list-style-type: none"> Operating: from 10% to 90% (non-condensing) Storage: from 5% to 95% (non-condensing)

Delivery Package	
<ul style="list-style-type: none"> Router DIR-2150 Power adapter DC 12V/2A Ethernet cable "Quick Installation Guide" (brochure) 	

Supported USB modems³	
GSM	<ul style="list-style-type: none"> · Alcatel X500 · D-Link DWM-152C1 · D-Link DWM-156A6 · D-Link DWM-156A7 · D-Link DWM 156A8 · D-Link DWM-156C1 · D-Link DWM-157B1 · D-Link DWM-157B1 (Velcom) · D-Link DWM-158D1 · D-Link DWR-710 · Huawei E150 · Huawei E1550 · Huawei E156G · Huawei E160G · Huawei E169G · Huawei E171 · Huawei E173 (Megafon) · Huawei E220 · Huawei E3131 (MTS 420S) · Huawei E352 (Megafon) · Prolink PHS600 · Prolink PHS901 · ZTE MF112 · ZTE MF192 · ZTE MF626 · ZTE MF627 · ZTE MF652 · ZTE MF667 · ZTE MF668 · ZTE MF752
LTE	<ul style="list-style-type: none"> · Alcatel IK40V · D-Link DWM-222 · Huawei E3131 · Huawei E3272 · Huawei E3351 · Huawei E3372s/E3372h-153 · Huawei E367 · Huawei E392 · Megafon M100-1 · Megafon M100-2 · Megafon M100-3 · Megafon M100-4 · Megafon M150-1 · Megafon M150-2 · Quanta 1K6E (Beeline 1K6E) · MTS 824F · MTS 827F · Yota LU-150 · Yota WLTUBA-107 · ZTE MF823 · ZTE MF827
Smartphones in USB tethering mode	<ul style="list-style-type: none"> · Some models of Android smartphones

*Specifications are subject to change without notice.
D-Link is a registered trademark of D-Link Corporation and its overseas subsidiaries. All other trademarks belong to their respective owners.*

³ The manufacturer does not guarantee proper operation of the router with every modification of the firmware of USB modems.