

## Product Highlights

### 802.11N

High connection rate  
(up to 300Mbps)  
and superior wireless range

### SECURITY

Multiple firewall functions,  
several security standards  
for wireless connection

### IPV6 SUPPORT

All needed functions  
for up-to-date networking



## DIR-615

### Wireless N300 Router

#### Wireless Interface

Using the DIR-615 device, you are able to quickly create a wireless network at home or in your office, which lets computers and mobile devices access the Internet virtually anywhere (within the operational range of your wireless network). The router can operate as a base station for connecting wireless devices of the standards 802.11b, 802.11g, and 802.11n (at the rate up to 300Mbps).

#### Secure Wireless Connection

The router supports multiple functions for the wireless interface: several security standards (WEP, WPA/WPA2), MAC address filtering, WPS, WMM.

#### Advanced Capabilities of Wireless Network

Support of guest Wi-Fi network allows you to create a separate wireless network with individual security settings and maximum rate limitation. Devices connected to the guest network will be able to access the Internet, but will be isolated from the devices and resources of the router's LAN.

#### 4-port Switch

The built-in 4-port switch enables you to connect Ethernet-enabled computers, game consoles, and other devices to your network.

#### Security

The wireless router DIR-615 includes a built-in firewall. The advanced security functions minimize threats of hacker attacks, prevent unwanted intrusions to your network, and block access to unwanted websites for users of your LAN.

Built-in Yandex.DNS service protects against malicious and fraudulent web sites and helps to block access to adult content on children's devices.

**Easy configuration and update**

You can configure the settings of the wireless router DIR-615 via the user-friendly web-based interface (the interface is available in several languages).

The configuration wizard allows you to quickly switch DIR-615 to one of the following modes: router (for connection to a wired or wireless ISP), access point, repeater, or client, and then configure all needed setting for operation in the selected mode in several simple steps.

Also DIR-615 supports configuration and management via mobile application for Android and iPhone smartphones.

You can simply update the firmware: the router itself finds approved firmware on D-Link update server and notifies when ready to install it.

Hardware	
Processor	<ul style="list-style-type: none"> <li>RTL8196E (400MHz)</li> </ul>
RAM	<ul style="list-style-type: none"> <li>32MB, DDR SDRAM</li> </ul>
Flash	<ul style="list-style-type: none"> <li>4MB, SPI</li> </ul>
Interfaces	<ul style="list-style-type: none"> <li>10/100BASE-TX WAN port</li> <li>4 10/100BASE-TX LAN ports</li> </ul>
LEDs	<ul style="list-style-type: none"> <li>Internet</li> <li>WLAN / WPS</li> <li>Power</li> </ul>
Buttons	<ul style="list-style-type: none"> <li>WPS/RESET button to set up wireless connection and restore factory default settings</li> </ul>
Antenna	<ul style="list-style-type: none"> <li>Two external non-detachable antennas (5dBi gain)</li> </ul>
MIMO	<ul style="list-style-type: none"> <li>2 x 2</li> </ul>
Power connector	<ul style="list-style-type: none"> <li>Power input connector (DC)</li> </ul>

Software	
WAN connection types	<ul style="list-style-type: none"> <li>PPPoE</li> <li>IPv6 PPPoE</li> <li>PPPoE Dual Stack</li> <li>Static IPv4 / Dynamic IPv4</li> <li>Static IPv6 / Dynamic IPv6</li> <li>PPPoE + Static IP (PPPoE Dual Access)</li> <li>PPPoE + Dynamic IP (PPPoE Dual Access)</li> <li>PPTP/L2TP + Static IP</li> <li>PPTP/L2TP + Dynamic IP</li> </ul>
Network functions	<ul style="list-style-type: none"> <li>DHCP server/relay</li> <li>Advanced configuration of built-in DHCP server</li> <li>Stateful/Stateless mode for IPv6 address assignment, IPv6 prefix delegation</li> <li>Automatic obtainment of LAN IP address (for access point/repeater/client modes)</li> <li>DNS relay</li> <li>Dynamic DNS</li> <li>Static IPv4/IPv6 routing</li> <li>IGMP Proxy</li> <li>Support of UPnP IGD</li> <li>Support of VLAN</li> <li>WAN ping respond</li> <li>Support of SIP ALG</li> <li>Support of RTSP</li> <li>WAN failover</li> <li>Autonegotiation of speed, duplex mode, and flow control / Manual speed and duplex mode setup for each Ethernet port</li> <li>Setup of maximum TX rate for each port of the router</li> </ul>
Firewall functions	<ul style="list-style-type: none"> <li>Network Address Translation (NAT)</li> <li>Stateful Packet Inspection (SPI)</li> <li>IPv4/IPv6 filter</li> <li>MAC filter</li> <li>URL filter</li> <li>DMZ</li> <li>Prevention of ARP and DDoS attacks</li> <li>Virtual servers</li> <li>Built-in Yandex.DNS web content filtering service</li> </ul>
VPN	<ul style="list-style-type: none"> <li>IPsec/PPTP/L2TP/PPPoE pass-through</li> <li>PPTP/L2TP tunnels</li> </ul>
Management and monitoring	<ul style="list-style-type: none"> <li>Local and remote access to settings through TELNET/WEB (HTTP/HTTPS)</li> <li>Multilingual web-based interface for configuration and management</li> <li>Support of D-Link Assistant application for Android and iPhone smartphones</li> <li>Notification on connection problems and auto redirect to settings</li> <li>Firmware update via web-based interface</li> <li>Automatic notification on new firmware version</li> <li>Saving/restoring configuration to/from file</li> <li>Support of logging to remote host</li> <li>Automatic synchronization of system time with NTP server and manual time/date setup</li> <li>Ping utility</li> <li>Traceroute utility</li> <li>TR-069 client</li> <li>Automatic reboot on schedule</li> </ul>

Wireless Module Parameters	
<b>Standards</b>	<ul style="list-style-type: none"> <li>IEEE 802.11b/g/n</li> </ul>
<b>Frequency range</b>  <i>The frequency range depends upon the radio frequency regulations applied in your country</i>	<ul style="list-style-type: none"> <li>2400 ~ 2483.5MHz</li> </ul>
<b>Wireless connection security</b>	<ul style="list-style-type: none"> <li>WEP</li> <li>WPA/WPA2 (Personal/Enterprise)</li> <li>MAC filter</li> <li>WPS (PBC)</li> </ul>
<b>Advanced functions</b>	<ul style="list-style-type: none"> <li>Support of client mode</li> <li>WMM (Wi-Fi QoS)</li> <li>Information on connected Wi-Fi clients</li> <li>Advanced settings</li> <li>Guest Wi-Fi / support of MBSSID</li> <li>Rate limitation for wireless network/separate MAC addresses</li> <li>Periodic scan of channels, automatic switch to least loaded channel</li> <li>Autonegotiation of channel bandwidth in accordance with environment conditions (20/40 Coexistence)</li> </ul>
<b>Wireless connection rate</b>	<ul style="list-style-type: none"> <li>IEEE 802.11b: 1, 2, 5.5, and 11Mbps</li> <li>IEEE 802.11g: 6, 9, 12, 18, 24, 36, 48, and 54Mbps</li> <li>IEEE 802.11n: from 6.5 to 300Mbps (from MCS0 to MCS15)</li> </ul>
<b>Transmitter output power</b>  <i>The maximum value of the transmitter output power depends upon the radio frequency regulations applied in your country</i>	<ul style="list-style-type: none"> <li>802.11b (typical at room temperature 25 °C) 15dBm at 1, 2, 5.5, 11Mbps</li> </ul>
<b>Receiver sensitivity</b>	<ul style="list-style-type: none"> <li>802.11n (typical at PER = 10% at room temperature 25 °C) HT20 -74dBm at MCS7/15 HT40 -71.5dBm at MCS7/15</li> </ul>
<b>Modulation schemes</b>	<ul style="list-style-type: none"> <li>802.11b: DQPSK, DBPSK, and CCK</li> <li>802.11g: BPSK, QPSK, 16QAM, 64QAM, OFDM</li> <li>802.11n: BPSK, QPSK, 16QAM, 64QAM with OFDM</li> </ul>

Physical Parameters	
<b>Dimensions (L x W x H)</b>	<ul style="list-style-type: none"> <li>158 x 131 x 36 mm (6.2 x 5.2 x 1.4 in)</li> </ul>

Operating Environment	
<b>Power</b>	<ul style="list-style-type: none"> <li>Output: 5V DC, 1A</li> </ul>
<b>Temperature</b>	<ul style="list-style-type: none"> <li>Operating: from 0 to 40 °C</li> <li>Storage: from -20 to 65 °C</li> </ul>
<b>Humidity</b>	<ul style="list-style-type: none"> <li>Operating: from 10% to 90% (non-condensing)</li> <li>Storage: from 5% to 90% (non-condensing)</li> </ul>

Delivery Package	
<ul style="list-style-type: none"> <li>Router DIR-615</li> <li>Power adapter DC 5V/1A</li> <li>Ethernet cable</li> <li>"Quick Installation Guide" (brochure)</li> </ul>	