

Product Highlights

Wi-Fi 6 (802.11ax)

Less network congestion and faster speed – total wireless connection rate up to 1800Mbps¹

SECURITY

Multiple firewall functions, several security standards for wireless connection

IPV6 SUPPORT

All needed functions for up-to-date networking



DIR-X1860

AX1800 Wi-Fi 6 EasyMesh Gigabit Router

Wireless Interface

Support of Wi-Fi 6 (802.11ax) standard provides faster speeds, greater capacity, and less network congestion for high-performance device-dense environments. It ensures connection of more devices and prevents weakening wireless connectivity by wall obstruction and interference from other appliances.

Using the DIR-X1860 device, you are able to quickly create a high-speed wireless network at home or in your office, which lets computers and mobile devices access the Internet virtually anywhere (within the operational range of your wireless network). Simultaneous activity of 2.4GHz band and 5GHz band allows performing a wide range of tasks. The router can operate as a base station for connecting wireless devices of the standards 802.11a, 802.11b, 802.11g, 802.11n, 802.11ac, and 802.11ax (at the wireless connection rate up to 1775Mbps¹).

Secure Wireless Connection

The router supports multiple functions for the wireless interface: several security standards (WEP, WPA/WPA2/WPA3), MAC address filtering, WPS, WMM.

In addition, the device is equipped with a button for switching the Wi-Fi network off/on. If needed, for example, when you leave home, you can easily switch the router's WLAN by pressing the button, and devices connected to the LAN ports of the router will stay online.

¹ Up to 574Mbps for 2.4GHz and up to 1201Mbps for 5GHz.

Advanced Capabilities of Wireless Network

The Band Steering technology simplifies connection to the network and optimizes further operation for the wireless clients. You can configure the wireless network with one name for both bands, so the clients automatically choose the preferred band when they are connecting or when the network conditions change.

The EasyMesh function allows to quickly connect several² DIR-X1860 devices into one transport network, for example, when it's required to provide high-quality Wi-Fi coverage without dead zones in living units of complicated planning or it's needed to create a large temporary Wi-Fi network for an outdoor event.

Multi-user MIMO technology allows to distribute the router's resources to let multiple wireless clients use the Wi-Fi network efficiently, keeping high rates for HD media streaming, lag-free gaming, and fast transfer of large files.

Transmit Beamforming technology allows to flexibly change the antennas' radiation pattern and to redistribute the signal directly to wireless devices connected to the router.

Smart adjustment of Wi-Fi clients is useful for networks based on several D-Link access points or routers – when the smart adjustment function is configured on each of them, a client always connects to the access point (router) with the highest signal level.

Support of guest Wi-Fi network allows you to create a separate wireless network with individual security settings. Devices connected to the guest network will be able to access the Internet, but will be isolated from the devices and resources of the router's LAN.

LAN/WAN Conversion, WAN Failover

You can use any Ethernet port of the router as LAN or WAN port. The new-generation firmware supports assigning several WAN ports, for example, in order to configure the primary and backup WAN connection of different ISPs.

Security

The wireless router DIR-X1860 includes a built-in firewall. The advanced security functions minimize threats of hacker attacks and prevent unwanted intrusions to your network, and block access to unwanted websites for users of your LAN.

The SSH protocol support provides more secure remote configuration and management of the router due to encryption of all transmitted traffic, including passwords.

The router supports multiple types of secure VPN connection tunnels: IPsec (IKEv1/IKEv2), L2TP over IPsec, PPTP/L2TP, GRE, IPIP, EoGRE, EoIP, OpenVPN, and WireGuard tunnels.

The router also supports the SkyDNS web content filtering service, which provides more settings and opportunities for safer Internet experience for home users of all ages and for professional activities of corporate users.

Now the schedules are also implemented; they can be applied to the rules and settings of the firewall and used to reboot the router at the specified time or every specified time period and to enable/disable the wireless network and the Wi-Fi filter.

The new ad blocking function effectively blocks advertisements which appear during web surfing.

Easy configuration and update

You can configure the settings of the wireless router DIR-X1860 via the user-friendly web-based interface (the interface is available in two languages – in Russian and in English).

The configuration wizard allows you to quickly switch DIR-X1860 to one of the following modes: router (for connection to a wired or wireless ISP), access point, repeater, or client, and then configure all needed setting for operation in the selected mode in several simple steps.

Also DIR-X1860 supports configuration and management via mobile application for Android smartphones.

You can simply update the firmware: the router itself finds approved firmware on D-Link update server and notifies when ready to install it.

² Up to 6 DIR-X1860 devices with FW version 4.0.5 or higher.

Hardware	
Processor	<ul style="list-style-type: none"> MT7621AT (880MHz, dual core)
RAM	<ul style="list-style-type: none"> 256MB, DDR3L SDRAM
Flash	<ul style="list-style-type: none"> 128MB, NAND
Interfaces	<ul style="list-style-type: none"> 10/100/1000BASE-T WAN port 3 10/100/1000BASE-T LAN ports
LEDs	<ul style="list-style-type: none"> Power Internet WLAN 2.4G WLAN 5G
Buttons	<ul style="list-style-type: none"> POWER button to power on/power off RESET button to restore factory default settings WPS button to connect mesh network devices, set up wireless connection, and enable/disable wireless network
Antenna	<ul style="list-style-type: none"> Two external non-detachable antennas for 2.4GHz band (5dBi gain) Two external non-detachable antennas for 5GHz band (5dBi gain)
MIMO	<ul style="list-style-type: none"> 2 x 2, MU-MIMO
Power connector	<ul style="list-style-type: none"> Power input connector (DC)
Mounting	<ul style="list-style-type: none"> Desktop Wall

Software	
WAN connection types	<ul style="list-style-type: none"> PPPoE IPv6 PPPoE PPPoE Dual Stack Static IPv4 / Dynamic IPv4 Static IPv6 / Dynamic IPv6 PPPoE + Static IP (PPPoE Dual Access) PPPoE + Dynamic IP (PPPoE Dual Access) PPTP/L2TP + Static IP PPTP/L2TP + Dynamic IP L2TP Dual Stack 6in4 6to4 6rd
Network functions	<ul style="list-style-type: none"> DHCP server/relay Advanced configuration of built-in DHCP server Stateful/Stateless mode for IPv6 address assignment, IPv6 prefix delegation Automatic obtainment of LAN IP address (for access point/repeater/client modes) DNS relay Dynamic DNS Static IPv4/IPv6 routing IGMP/MLD Proxy RIP Support of UPnP Support of VLAN WAN ping respond Support of SIP ALG Support of RTSP WAN failover LAN/WAN conversion Multi-WAN support Autonegotiation of speed, duplex mode, and flow control / Manual speed and duplex mode setup for each Ethernet port Built-in UDPXY application Equal load distribution while using several WAN connections (traffic balancing) Support of VRRP Port mirroring Wake-on-LAN support

Software	
Firewall functions	<ul style="list-style-type: none"> · Network Address Translation (NAT) · Stateful Packet Inspection (SPI) · IPv4/IPv6 filter · MAC filter · URL filter · Ad blocking function · DMZ · Virtual servers · Built-in SkyDNS web content filtering service
VPN	<ul style="list-style-type: none"> · IPsec/PPTP/L2TP/PPPoE pass-through · PPTP/L2TP servers · PPTP/L2TP tunnels · OpenVPN server/tunnels with PKI option (certificates/keys) · L2TP over IPsec client · GRE/EoGRE/EoIP/IPIP/WireGuard tunnels · IPsec tunnels · Transport/Tunnel mode · IKEv1/IKEv2 support · DES/3DES/AES/BLOWFISH/CAMELLIA/SERPENT/TWOFISH encryption · NAT Traversal · Support of DPD (Keep-alive for VPN tunnels)
Management and monitoring	<ul style="list-style-type: none"> · Local and remote access to settings through SSH/TELNET/WEB (HTTP/HTTPS) · Bilingual web-based interface for configuration and management (Russian/English) · Support of D-Link Assistant application for Android smartphones · Notification on connection problems and auto redirect to settings · Firmware update via web-based interface · Automatic notification on new firmware version · Saving/restoring configuration to/from file · Support of logging to remote host · Automatic synchronization of system time with NTP server and manual time/date setup · Ping utility · Traceroute utility · TR-069 client · SNMP agent · Schedules for rules and settings of firewall, automatic reboot, and enabling/disabling wireless network and Wi-Fi filter · Automatic upload of configuration file from ISP's server (Auto Provision) · Configuration of action for hardware buttons

Wireless Module Parameters	
Standards	<ul style="list-style-type: none"> · IEEE 802.11ax · IEEE 802.11ac Wave 2 · IEEE 802.11a/b/g/n
Frequency range <i>The frequency range depends upon the radio frequency regulations applied in your country</i>	<ul style="list-style-type: none"> · 2400 ~ 2483.5MHz · 5150 ~ 5350MHz · 5650 ~ 5850MHz
Wireless connection security	<ul style="list-style-type: none"> · WEP · WPA/WPA2 (Personal/Enterprise) · WPA3 (Personal) · MAC filter · WPS (PBC/PIN)

Wireless Module Parameters	
Advanced functions	<ul style="list-style-type: none"> · EasyMesh function · Support of client mode · WMM (Wi-Fi QoS) · Information on connected Wi-Fi clients · Advanced settings · Smart adjustment of Wi-Fi clients · Guest Wi-Fi / support of MBSSID · Periodic scan of channels, automatic switch to least loaded channel · Support of 2.4GHz/5GHz TX Beamforming · Autonegotiation of channel bandwidth in accordance with environment conditions (20/40 Coexistence) · Support of STBC · CoovaChilli authentication portal · Support of OFDMA technology · Support of TWT technology · Support of Band Steering · Support of Airtime Fairness
Wireless connection rate³	<ul style="list-style-type: none"> · IEEE 802.11a: 6, 9, 12, 18, 24, 36, 48, and 54Mbps · IEEE 802.11b: 1, 2, 5.5, and 11Mbps · IEEE 802.11g: 6, 9, 12, 18, 24, 36, 48, and 54Mbps · IEEE 802.11n (2.4GHz/5GHz): from 6.5 to 300Mbps (MCS0–MCS15) · IEEE 802.11ac (5GHz): from 6.5 to 867Mbps · IEEE 802.11ax (2.4GHz): from 6.5 to 574Mbps · IEEE 802.11ax (5GHz): from 6.5 to 1201Mbps
Transmitter output power <i>The maximum value of the transmitter output power depends upon the radio frequency regulations applied in your country</i>	<ul style="list-style-type: none"> · Less than 20dBm (100mW)
Receiver sensitivity	<ul style="list-style-type: none"> · 802.11a (typical at PER < 10% (1000-byte PDUs) at room temperature 25 °C) <ul style="list-style-type: none"> -92dBm at 6Mbps -90dBm at 9Mbps -89dBm at 12Mbps -87dBm at 18Mbps -84dBm at 24Mbps -80dBm at 36Mbps -76dBm at 48Mbps -74dBm at 54Mbps · 802.11b (typical at PER = 8% (1000-byte PDUs) at room temperature 25 °C) <ul style="list-style-type: none"> -96dBm at 1Mbps -94dBm at 2Mbps -91dBm at 5.5Mbps -88dBm at 11Mbps · 802.11g (typical at PER < 10% (1000-byte PDUs) at room temperature 25 °C) <ul style="list-style-type: none"> -92dBm at 6Mbps -90dBm at 9Mbps -89dBm at 12Mbps -87dBm at 18Mbps -84dBm at 24Mbps -80dBm at 36Mbps -77dBm at 48Mbps -75dBm at 54Mbps · 802.11n (typical at PER = 10% (1000-byte PDUs) at room temperature 25 °C) <ul style="list-style-type: none"> 2.4GHz, HT20 -92dBm at MCS0/8 -89dBm at MCS1/9 -87dBm at MCS2/10 -84dBm at MCS3/11 -80dBm at MCS4/12 -76dBm at MCS5/13 -75dBm at MCS6/14 -73dBm at MCS7/15

³ Maximum wireless signal rate is derived from IEEE standard 802.11ax and 802.11ac specifications. In order to get the rate of 574Mbps in the 2.4GHz band, a Wi-Fi client should support 802.11ax, HE40 mode with MIMO 2x2, and 1024-QAM modulation. Actual data throughput will vary. Network conditions and environmental factors, including volume of network traffic, building materials and construction, and network overhead, lower actual data throughput rate. Environmental factors will adversely affect wireless signal range.

Wireless Module Parameters

2.4GHz, HT40
 -89dBm at MCS0/8
 -86dBm at MCS1/9
 -83dBm at MCS2/10
 -80dBm at MCS3/11
 -78dBm at MCS4/12
 -74dBm at MCS5/13
 -72dBm at MCS6/14
 -70dBm at MCS7/15

5GHz, HT20
 -92dBm at MCS0/8
 -89dBm at MCS1/9
 -86dBm at MCS2/10
 -83dBm at MCS3/11
 -79dBm at MCS4/12
 -76dBm at MCS5/13
 -74dBm at MCS6/14
 -72dBm at MCS7/15

5GHz, HT40
 -88dBm at MCS0/8
 -85dBm at MCS1/9
 -83dBm at MCS2/10
 -80dBm at MCS3/11
 -76dBm at MCS4/12
 -72dBm at MCS5/13
 -70dBm at MCS6/14
 -68dBm at MCS7/15

802.11ac (typical at PER = 10% (1000-byte PDUs) at room temperature 25 °C)

VHT20
 -91dBm at MCS0
 -89dBm at MCS1
 -87dBm at MCS2
 -84dBm at MCS3
 -80dBm at MCS4
 -76dBm at MCS5
 -74dBm at MCS6
 -72dBm at MCS7
 -68dBm at MCS8

VHT40
 -90dBm at MCS0
 -86dBm at MCS1
 -84dBm at MCS2
 -81dBm at MCS3
 -77dBm at MCS4
 -73dBm at MCS5
 -72dBm at MCS6
 -70dBm at MCS7
 -67dBm at MCS8
 -65dBm at MCS9

VHT80
 -86dBm at MCS0
 -83dBm at MCS1
 -81dBm at MCS2
 -78dBm at MCS3
 -74dBm at MCS4
 -70dBm at MCS5
 -68dBm at MCS6
 -66dBm at MCS7
 -63dBm at MCS8
 -61dBm at MCS9

Wireless Module Parameters

- 802.11ax (typical at PER = 10% (1000-byte PDUs) at room temperature 25 °C)
- 2.4GHz, HE20
- 90dBm at HE0
- 89dBm at HE1
- 85dBm at HE2
- 83dBm at HE3
- 80dBm at HE4
- 78dBm at HE5
- 76dBm at HE6
- 73dBm at HE7
- 72dBm at HE8
- 68dBm at HE9
- 64dBm at HE10
- 61dBm at HE11
- 2.4GHz, HE40
- 90dBm at HE0
- 88dBm at HE1
- 85dBm at HE2
- 83dBm at HE3
- 80dBm at HE4
- 76dBm at HE5
- 74dBm at HE6
- 72dBm at HE7
- 69dBm at HE8
- 67dBm at HE9
- 64dBm at HE10
- 61dBm at HE11
- 5GHz, HE20
- 89dBm at HE0
- 88dBm at HE1
- 86dBm at HE2
- 83dBm at HE3
- 80dBm at HE4
- 78dBm at HE5
- 76dBm at HE6
- 74dBm at HE7
- 70dBm at HE8
- 68dBm at HE9
- 65dBm at HE10
- 63dBm at HE11
- 5GHz, HE40
- 88dBm at HE0
- 86dBm at HE1
- 84dBm at HE2
- 81dBm at HE3
- 78dBm at HE4
- 74dBm at HE5
- 73dBm at HE6
- 71dBm at HE7
- 67dBm at HE8
- 65dBm at HE9
- 62dBm at HE10
- 60dBm at HE11
- 5GHz, HE80
- 84dBm at HE0
- 81dBm at HE1
- 79dBm at HE2
- 75dBm at HE3
- 73dBm at HE4
- 71dBm at HE5
- 70dBm at HE6
- 68dBm at HE7
- 63dBm at HE8
- 61dBm at HE9
- 59dBm at HE10
- 56dBm at HE11

Physical Parameters	
Dimensions (L x W x H)	· 174 x 139 x 60 mm (6.85 x 5.47 x 2.36 in)
Weight	· 280 g (0.62 lb)

Operating Environment	
Power	· Output: 12V DC, 1A
Temperature	· Operating: from 0 to 40 °C · Storage: from -20 to 65 °C
Humidity	· Operating: from 10% to 90% (non-condensing) · Storage: from 5% to 95% (non-condensing)

Delivery Package	
· Router DIR-X1860 · Power adapter DC 12V/1A · Ethernet cable · "Quick Installation Guide" (brochure)	