





Bluetooth USB Printer Adapter

For Wireless Printing From Laptops, PDA, Mobile Phone

The D-Link PersonalAir DBT-320 Bluetooth USB Printer Adapter allows you to convert your USB printer into a Bluetooth wireless device. It gives you the mobile freedom and instant wireless access to your USB printer. The DBT-320 connects directly to your printer through the USB for a plug and play experience. All you need to start printing wirelessly with the DBT-320 is a Bluetooth-enabled mobile device such as your laptop, PDA, or mobile phone.

Bluetooth Personal Area Network

The DBT-320 allows you to add a printer to your Bluetooth Personal Area Network (PAN) for communication between all your personal mobile devices. The DBT-320 supports standard Bluetooth profiles for printing including the Hardcopy Cable Replacement Profile (HCRP), Serial Port Profile (SPP), and Object Push Profile (OPP), which mean printing compatibility with virtually all Bluetooth-enabled mobile devices. It gives you the convenience of wireless printing from your PDA, mobile phone, laptop, and computers.

Convenient & Low-Cost Wireless Connection for Home and Office

The DBT-320 is great for home and office use, freeing you from cables and wires. It is based on a low-cost, short-range radio link, connecting many types of digital devices such as your computers and mobile phones, without a single cable in sight, giving you more freedom to roam about freely.

As the DBT-320 utilizes a radio-based link, it does not require a line-of-sight connection in order to communicate with devices, something needed when using an Infra-red connection. This allows you use your laptop in one room and send a document to the printer in another room some distance away. In order to print, your Bluetooth-enabled computer, PDA or mobile phone simply has to come within a 10-meter range of your printer. **

* PCL3 printer required for PDA and mobile phone printing. PDA printing software required depending on your PDA model.

Standards & Features

- Wireless printing from laptop computers, PDAs, mobile phones
- Enables upgrading of USB printers to Bluetooth-enabled
- Simply plugs to printer's USB port, no driver program required
- Works with all popular USB printers
- Works with all popular Bluetooth-enabled mobile phones such as Sony Ericsson & PDAs with OPP support
- Works with Windows 98SE, 2000, ME, XP computers with Bluetooth HCRP support
- Supports HCRP and OPP Profile to provide wireless printing for Bluetooth-enabled computers, notebooks, Mac
- USB1.1 and Bluetooth 1.1 compliant
- Wireless range 10 meters *

^{**} Environmental factors may adversely affection operation range.

DBT-320

Technical Specifications

Standards

- Bluetooth: v1.1
- USB: 1.1

USB Port

Type B

Bluetooth Profile Support

- HCRP (Hardcopy Cable Replacement Profile)
- SPP (Serial Port Profile)
- OPP (Object Push Profile)

O.S. Support

Microsoft Windows 98, 2000, ME, XP

System Requirements

- Bluetooth Enabled PC, Mobile Phone, or PDA*
- Printing Software for PDA Printing
- Printer with USB Type B Port
- * PCL3 printer required for PDA and mobile phone printing. PDA printing software required depending on your PDA model.

Radio Class

Class 2

Spread Spectrum

FHSS (Frequency Hopping Spread Spectrum)

Modulation Type

GFSK (Gaussian Frequency Shift Keying)

Frequency Band

2400 to 2483.5 MHz USA & Europe (except France)

Frequency Hopping

1600hops/sec (or 625 nanosecond/hop)

Receiving Sensitivity

-76 to -82 dBm

RF Output Power

-6 to +4 dBm (Class 2)

Receiving Signal Range

Better than -76 dBm @ 0.1% FER

Antenna

1.8 dBi Gain

Antenna Type

Dipole Antenna

Operating Distance

Up to 10 meters *

Physical & Environmental

Supply Voltage

Operation Current

80mA (max.)

AC 100 to 240VAC, 50/60Hz (through external AC power adapter)

Output Power

DC +5V, 2.1A

Power Consumption

0.7 watts @ 5V DC

Dimensions

89 x 52 x 28 mm (device only, without Antenna and USB cable)

Operating Temperature

0° to 55 °C

Storage Temperature

-10° to 85 °C

Bluetooth Printer Adapter

Box Includes

- DBT-320 device
- External power adapter
- Quick Installation Guide





Ordering Information

DBT-320 Bluetooth USB Printer Adapter

Please specify your order as follows:

DBT-320/A With North America standard power adapter With EU standard power adapter **DBT-320/E DBT-320/B** With UK standard power adapter **DBT-320/N** With Australia standard power adapter **NDBT-320** For China

TDBT-320 For Taiwan **BDBT-320** For USA



RECYCLABLE

Rev. 01 (Jun. 2004)

TEL: 1-714-885-6000 TEL: 1-905-8295033 TEL: 44-20-8731-5555 Europe Germany TEL: 49-6196-77990 TEL: 33-1-30238688 France TEL: 31-10-282-1445 TEL: 32(0)2-517-7111 Netherlands Belgium Italy Iberia Sweden Norway Denmark Singapore Australia Japan China Middle East (Dubai) TEL: 9714-8834234

India Turkey Egypt Latinamerica Brasil South Africa Russia D-Link Corp.

TEL: 39-2-2900-0676 TEL: 34-93-4090770 TEL: 46-(0)8564-61900 TEL: 47-22-309075 TEL: 45-43-969040 TEL: 358-9-2707-5080 TEL: 65-6774-6233 TEL: 61-2-8899-1800 TEL: 81-3-5434-9678 TEL: 86-10-8518-2533 TEL: 91-022-652-6696 TEL: 90-212-335-2553 TEL: 202-414-4295 TEL: 972-9-9715700 TEL: 56-2-232-3185 TEL: 55-11-55039320 TEL: 27(0)1266-52165 TEL: 7-095-744-0099 TEL: 886-2-2910-2626 TEL: 886-2-2916-1600 FAX: 1-866-743-4905 FAX: 1-905-8295223 FAX: 44-20-8731-5511 FAX: 49-6196-7799300 FAX: 33-1-30238689 FAX: 31-10-282-1331 FAX: 32(0)2-517-6500 FAX: 39-2-2900-1723 FAX: 34-93-4910795 FAX: 46-(0)8564-61901 FAX: 47-22-309085 FAX: 45-43-424347 FAX: 358-9-2707-5081 FAX: 65-6774-6322 FAX: 61-2-8899-1868 FAX: 81-3-5434-9868 FAX: 86-10-8518-2250 FAX: 91-022-652-8914 FAX: 9714-8834394 FAX: 90-212-335-2500 FAX: 202-415-6704 FAX: 972-9-9715601 FAX: 56-2-232-0923 FAX: 55-11-55039321 FAX: 270)1266-52186

FAX: 7-095-744-0099#350

FAX: 886-2-2914-6299

^{*} Environmental factors may adversely affection operation range