





# **802.11g High-Speed Router/AP**

The DWL-G730AP Wireless Compact Router/AP is a portable and convenient wireless solution for the traveling business person delivering 802.11g wireless connectivity with a maximum wireless signal rate of up to 54Mbps. This comact-sized device is very convenient for use it in conference rooms, hotel rooms, or even at hotspots. This portable wireless networking solution is especially designed for business travelers wanting to access and share hotel Internet connections, wirelessly connect Ethernet devices or secure shared information from potential hackers.

### **Dual Access Points & Router Functions**

The Wireless Compact Router/APmight be small in size, but is huge in functionality. The DWL-G730AP supports multiple operation modes including: Access Point (AP) mode to create a wireless connection; Router mode to share an Internet connection; and Wireless Client mode to connect an existing wireless network. Easily switch between these modes by using the 3-way configuration switch located at the bottom.

In AP mode, the DWL-G730AP can be used to create a wireless network in a room where a single Ethernet port is provided. Now multiple wireless clients can connect to the network at the same time to share resources and files.

In Router mode, the DWL-G730AP can be used to share a single broadband Internet connection, such as in a hotel room. The internal DHCP server automatically assigns IP addresses to ensure everyone in the room can connect to the Internet. In addition, the DWL-G730AP supports VPN Passthrough and firewall features including Network Address Translation (NAT) and MAC filtering to protect your wireless network from malicious attacks.

#### Wireless Connections Without AC Power Source

When set in Wireless Client mode, the DWL-G730AP allows connection to an existing wireless network, without having to install complicated drivers or additional software. For added mobility, the DWL-G730AP can be powered over USB if power outlets are not available.

## **Enhanced Network Security**

The Compact Router/AP supports WPA-PSK to secure your wireless data communications. In AP mode, the DWL-G730AP adds support for 802.1x user authentication with an external RADIUS server. For setup and configuration the DWL-G730AP can be accessed via D-Link's user-friendly Web-based utility.

### **Convenient For Traveling**

The DWL-G730AP is smaller than the average PDA, easy to pack and convenient for traveling. It comes with an attractive traveling case, which also provides accessories including cables and a power adapter.

\* Maximum wireless signal rate based on IEEE Standard 802.11g specifications. Actual data throughput will vary. Network conditions and environmental factors lower actual data throughput rate.

#### **Features**

- Portable 802.11g wireless connectivity
- Up to 54Mbps wireless speed
- Compact-sized, lightweight, ideal for traveling
- Can be used as an access point, wireless router, or wireless client
- Includes convenient travel case
- Supports power over USB

## *DWL-G730AP*

# **Technical Specifications**

#### **Standards**

- IEEE 802.11b
- IEEE 802.11g
- IEEE 802.3
- IEEE 802 3u

#### **Network Data Transfer Rates**

- For 802.11g:
- 54, 48, 36, 24, 18, 12, 9 and 6Mbps
- For 802.11b:
- 11, 5.5, 2, and 1Mbps

#### Wireless Frequency Range

2.412GHz to 2.462GHz

#### Wireless Operating Range \*

(802.11g full power with internal antenna, outdoors)

- 50 m (164ft) @ 54Mbps
- 150 m (492ft) @ 11Mbps
- 200 m (656ft) @ 6Mbps
- \* Environmental factors may affect operation range.

#### Radio and Modulation Type (for 802.11g)

- OFDM:

BPSK @ 6 and 9Mbps

QPSK @ 12 and 18Mbps

16QAM @ 24 and 36Mbps

64QAM @ 48 and 54Mbps - DSSS:

DBPSK @ 1Mbps

DQPSK @ 2Mbps CCK @ 5.5 and 11Mbps

#### Radio and Modulation Type (for 802.11b)

DBPSK @ 1Mbps

DQPSK @ 2Mbps

CCK @ 5.5 and 11Mbps

#### **Wireless Transmit Power**

(Typical RF Output Power at each Data Rate)

- For 802.11g:

31mW (15dBm) @ 54Mbps

40mW (16dBm) @ 48Mbps

40mW (16dBm) @ 36, 24, 18, 12, 9, and 6Mbps

- For 802.11b:

50mW (17dBm) @ 11, 5.5, 2, and 1Mbps

#### **Receiver Sensitivity**

- For 802.11g:

6Mbps: -87dBm

9Mbps: -85dBm

12Mbps: -82dBm 18Mbps: -81dBm

24Mbps: -80dBm

36Mbps: -79dBm

48Mbps: -71dBm

54Mbps: -69dBm

- For 802.11b:

1Mbps: -90dBm 2Mbps: -90dBm

5.5Mbps: -86dBm

11Mbps: -85dBm

#### Security

- 64/128-bit WEP data encryption
- WPAPSK security
- MAC address filtering
- SSID broadcast disable

#### **Device Management**

Web-Based Internet Explorer v.6 or Netscape Navigator v.7

#### Physical & Environmental

## LEDs

- Power
- LAN
- WLAN

External Power Supply DC 5V/1.2A

# 2.4GHz Wireless LAN

80 (L) x 60 (W) x 17 (H) mm (3.15 x 2.36 x 0.67 inches)

#### Weight

50 grams (0.11 lb)

#### **Operating Temperature**

0° to 55 °C (32° to 131 °F)

#### Storage Temperature

-20° to 65 °C (-4° to 149 °F)

### **Operating Humidity**

10% to 90% (non-condensing)

#### **Storage Humidity**

5% to 95% (non-condensing)

#### Certifications

- FCC Class B
- CE

# F© (ED

# Ordering Information

Canada Europe Germany

France Netherlands

Belgium Italy Iberia

Sweden

Norway Denmark

Finland

Singapore

Australia

Egypt Israel Latinamerica

South Africa Russia

D-Link Corp.

Japan China

India

Brasil

Taiwan

DWL-G730AP

802.11g Compact Router/AP

without prior notice.
D-Link is a registered trademark and
AirPlusG is a trademark of
D-Link Corporation/D-Link System Inc.
All other trademarks belong to their

Rev. 01(Oct. 2004)

TEL: 1-714-885-6000 TEL: 1-905-8295033 TEL: 44-20-8731-5555 TEL: 49-6196-77990 TEL: 33-1-30238688 TEL: 31-10-282-1445 TEL: 32(0)2-517-7111 TEL: 39-2-2900-0676 TEL: 34-93-4090770 TEL: 46-(0)8564-61900 TEL: 47-22-309075 TEL: 45-43-969040 TEL: 358-9-2707-5080 TEL: 65-6774-6233 TEL: 61-2-8899-1800 TEL: 81-3-5434-9678 TEL: 86-10-8518-2533 TEL: 91-022-652-6696 Middle East (Dubai) TEL: 9714-8834234 Turkey TEL: 90-212-335-2553 TEL: 202-414-4295 TEL: 972-9-9715700 TEL: 56-2-232-3185

TEL: 55-11-55039320

TEL: 27(0)1266-52165 TEL: 7-095-744-0099

TEL: 886-2-2910-2626

TEL: 886-2-2916-1600

FAX: 1-866-743-4905 FAX: 1-905-8295223 FAX: 44-20-8731-5511 FAX: 49-6196-7799300 FAX: 33-1-30238689 FAX: 31-10-282-1331 FAX: 32(0)2-517-6500 FAX: 39-2-2900-1723 FAX: 34-93-4910795 FAX: 46-(0)8564-61901 FAX: 47-22-309085 FAX: 45-43-424347 FAX: 358-9-2707-5081 FAX: 65-6774-6322 FAX: 61-2-8899-1868 FAX: 81-3-5434-9868 FAX: 86-10-8518-2250 FAX: 91-022-652-8914 FAX: 9714-8834394 FAX: 90-212-335-2500 FAX: 202-415-6704 FAX: 972-9-9715601 FAX: 56-2-232-0923 FAX: 55-11-55039321 FAX: 270)1266-52186 FAX: 7-095-744-0099#350 FAX: 886-2-2910-1515