

### Product Highlights

#### Connect up to 4 PCs

Manage several computers with one monitor, one keyboard and one mouse.

#### Switch between PCs quickly and easily

Switch between computers quickly and easily using the buttons located on the front panel, keyboard hot keys or desktop controller.

#### Hot-plugging

You don't need to turn your computers off before installing the device.



## DKVM-410H

### 4-Port KVM Switch with HDMI and USB Ports

#### Specifications

- HDMI & USB ports
- Up to 4 connected PCs
- Switching between PCs with the buttons located on the front panel, keyboard hot keys or desktop controller
- Two USB Type-A ports for connecting external devices
- Hot-plugging
- Autoscan mode

The D-Link DKVM-410H 4-port KVM switch with HDMI and USB ports allows you to manage up to four computers with one monitor, one keyboard and one mouse. The DKVM-410H requires no driver installation and can function without external power adapter connection by powering from USB port of your PC (the power adapter<sup>1</sup> can be used when connecting external device, for example, USB-disk, to the USB Type-A port of the DKVM-410H). This KVM switch supports hot-plugging - you don't need to turn your computers off before installing the device. The DKVM-410H allows you to switch between computers quickly and easily using the buttons located on the front panel, keyboard hot keys or desktop controller. The DKVM-410H supports autoscan mode, which provides automatic switching to the next PC after the scan interval expires.

<sup>1</sup> Not included in the package contents.

Technical Specifications	
<b>Hardware</b>	
Ports for connecting KVM cables	<ul style="list-style-type: none"> <li>• 4 HDMI ports</li> <li>• 4 USB Type-B ports</li> </ul>
Ports for connecting management console	<ul style="list-style-type: none"> <li>• Monitor (local): HDMI</li> <li>• Keyboard (local): USB Type-A</li> <li>• Mouse (local): USB Type-A</li> </ul>
KVM cable connectors for connecting PC	<ul style="list-style-type: none"> <li>• HDMI connector</li> <li>• USB Type-A connector</li> </ul>
Ports for connecting external devices	<ul style="list-style-type: none"> <li>• 2 USB Type-A ports</li> </ul>
Port for connecting desktop controller	<ul style="list-style-type: none"> <li>• Mini-USB Type-B port</li> </ul>
LEDs	<ul style="list-style-type: none"> <li>• 4 port LEDs for connected PCs</li> </ul>
Buttons	<ul style="list-style-type: none"> <li>• 4 port switching buttons</li> </ul>
Enclosure	<ul style="list-style-type: none"> <li>• Metal</li> </ul>
<b>General Specifications</b>	
Connected PCs	<ul style="list-style-type: none"> <li>• Up to 4</li> </ul>
Autoscan mode	<ul style="list-style-type: none"> <li>• Yes</li> </ul>
Switching between PCs	<ul style="list-style-type: none"> <li>• Switching buttons on the front panel</li> <li>• Hot keys</li> <li>• Desktop controller</li> </ul>
Sound notification of switching	<ul style="list-style-type: none"> <li>• Yes</li> </ul>
HDMI version	<ul style="list-style-type: none"> <li>• HDMI 2.0 HDCP 2.2</li> </ul>
Resolution	<ul style="list-style-type: none"> <li>• Up to 4096x2160 / 3840x2160 @ 60 Hz (4:2:0)</li> </ul>
<b>Physical Parameters</b>	
Dimensions (L x W x H)	<ul style="list-style-type: none"> <li>• 210 x 80 x 22 mm</li> </ul>
<b>Environmental Conditions</b>	
Power supply	<ul style="list-style-type: none"> <li>• From USB port on PC</li> <li>• Power adapter<sup>1</sup> when using external devices</li> </ul>
Temperature	<ul style="list-style-type: none"> <li>• Operating: 0 to 50 °C</li> <li>• Storage: -20 to 60 °C</li> </ul>
Humidity	<ul style="list-style-type: none"> <li>• 0% to 80% non-condensing</li> </ul>
<b>Order Information</b>	
<i>Part Number</i>	<i>Description</i>
DKVM-410H	4-Port KVM Switch with HDMI and USB Ports

<sup>1</sup> Not included in the package contents.